

CSP-204

CSP – 200 series are advanced, conventional fire alarm control panels in full conformance with the requirements of EN54. They are designed for the implementation of simple systems in small and medium-sized facilities. The built-in LCD simplifies the system's day-to-day operation, its installation procedure and periodical maintenance. The benefits of the SATEL control panels are their uncomplicated installation, their aesthetic appearance and the use of a single, standard 12 V battery as a backup power supply source.

- 4 detection circuits
- built-in LCD for easy day-to-day operation and system programming
- supports remote panels and virtual panels (using **CSP-ETH** interface)
- 4 control inputs with functionality programmed by the installer
- 4 outputs programmed by the installer which enable interaction with other systems
- supports fire and damage transmission devices
- built-in backup power supply interfacing with a single battery 12 V and AUX 24 V and 18 V power outputs 24 V i 18 V



Terminating resistor on the circuit for signalling devices	10 kΩ +/-5%
Number of detection circuits	4
Maximum resistance of the detection circuit	100 Ω (2 x 50 Ω)
Maximum number of detectors on the detection circuit	32
Maximum number of manual call points (ROP) on the circuit	10
Terminating resistor on the detection circuit	5,6 k Ω +/- 5%
Maximum detection current of the detection circuit	10
Maximum current in the circuit during an alarm	40
Current limiting level of the detection circuit	54
Maximum resistance of the circuit for alarm and fault signalling devices	75 Ω (2 x 37,5 Ω)
Number of external circuits for signalling devices	2
Working voltage of the circuits for signalling devices	24 V DC +/-15%
Maximum current of the circuits for signalling devices	180
Electrical parameters of relay outputs	1A / 30 V DC (NO lub NC)
Number of alarm transmission circuits	1
Working voltage of the alarm transmission circuit	24 V DC +/-15%
Maximum current of the alarm transmission circuit	180
Terminating resistor on the alarm transmission circuit	10 kΩ +/-5%
Number of fault transmission circuits	1
Working voltage of the fault transmission	24 V DC +/-15%
Maximum current of the fault transmission circuit	180
Terminating resistor on the fault transmission circuit	10 kΩ +/-5%
Number of programmable relay outputs	4
Stand-by supply: internal acid battery	12 V / 17 Ah
Stand-by supply: external acid battery	12 V / ≤24 Ah
Supply output AUX (only for connection of CSP-ETH module): with AC power supply failure	12 V DC +15%, -20%
Sealing of the casing	IP30
Maximum humidity	93±3%
Dimensions	324 x 382 x 108
Transit temperature range	-25...+55 °C
Normal mains power supply with mains voltage of	230 V AC +10%, -15% 50 Hz
Maximum current draw from the mains	0,5
Operating duration of the stand-by supply	72 h
Maximum charging current of the battery	1,4
Maximum internal apparent resistance of the battery (with cables and terminals in a circuit)	1
Current draw from the battery when detecting	100
Current draw from the battery when emitting an alarm	170
Current draw from an integrated AC power adapter when detecting	80
Current draw from an integrated AC power adapter when emitting an alarm	140
Operating temperature range	-5...+40 °C
Weight without the battery	<3
Events storage capacity	8999
Alarm counter capacity	9999
Clock battery	3 V (CR2032)
Output for communication with PC (service output)	Tak
Terminating resistor on terminals for communication with the remote panel	100
Output for communication with remote panel and CSP-ETH module	Tak
Supply output +24V	24 V DC +/-15% / 200 mA maks.
Supply output AUX (only for connecting CSP-ETH module): in standard mode	18 V DC +5%, -15%
Alarm resistor on the control input circuit	1 kΩ +/- 5%
Terminating resistor on the control input circuit	10 kΩ +/-5%
Number of programmable control inputs	4