

VERSA Plus

The **VERSA Plus** control panel is designed for protection of small and medium-sized premises. It allows you to create a wired or wireless system – it is compatible with **ABAX 2 (ACU-220, ACU-280)** and **ABAX (ACU-120, ACU-270)** as well as **MICRA (VERSA-MCU)** wireless systems controllers.

The **VERSA Plus** is the solution that combines features of several separate devices. Its motherboard integrates the following modules: Ethernet, cellular GSM/GPRS, PSTN dialer, voice and acoustic alarm verification. As a result, the **VERSA Plus** control panel enables communication via three channels (Ethernet, cellular network, PSTN), thus ensuring effective transfer of information.

- EN50131 Grade 2 compliance
- 4 programmable wired zones:
 - support for NO and NC type detectors, and roller shutter and shock detectors
 - support for EOL and 2EOL configuration
- additional tamper input, NC type
- 5 programmable wired outputs:
 - 2 high-current outputs
 - 2 low-current outputs, OC type
 - 1 relay output
- 3 power outputs
- output for connecting dedicated enclosure-mounted piezoelectric transducer (acoustic signaling)
- maximum number of programmable zones: 30
- maximum number of programmable outputs: 12
- system subdivision into 2 partitions:
 - each zone can be assigned to two partitions
- system control by means of:
 - keypads:
 - LED with mechanical keyboard – **VERSA LED**
 - LCD with mechanical keyboard – **VERSA-LCD, VERSA-LCDM**
 - wireless LCD with mechanical keyboard – **VERSA-KWRL2**
 - touchscreen – **INT-TSG2, INT-TSH2**
 - partition control module (**INT-CR** – using cards, key fobs and other passive transponders)
 - remote control keyfobs
 - mobile application **VERSA CONTROL**
 - phone (SMS, voice menu)
- integrated modules:
 - Ethernet (reporting to monitoring station, e-mail messaging, mobile application, remote programming)
 - cellular GSM/GPRS (reporting to monitoring station, voice/SMS messaging, SMS/voice menu remote control, mobile application, remote programming)
 - PSTN dialer (reporting to monitoring station, voice messaging, voice menu remote control, remote programming)
 - voice (playback of voice messages for the needs of telephone messaging and voice menu)
 - audio alarm verification (listening in)
- built-in USB MINI-B socket, for programming the control panel and updating its firmware using a computer
- memory of 2047 events
- capability to handle 30 users and assign to each of them:
 - code
 - proximity card or other passive transponder
 - keyfob
- 4 timers to enable automatic:
 - arming/disarming partitions



- control of outputs (turning light ON/OFF, watering garden, etc.)
- plug-in terminal blocks

Notification e-mail addresses	8
Programmable wired outputs	5
Maximum number of programmable outputs	12
Supplying outputs	3
Communication buses	1
Keypads	do 6
Security grade according to EN 50131	Grade 2
Recommended transformer	40 VA
Mass (incl. enclosure and accessories)	1250
Users	30
Maximum number of programmable inputs	30
Text messages	64
Current-carrying capacity of KPD output	500 mA / 12 V DC
Output voltage range	10,5 V...14 V DC
Battery charging current	800
Low current programmable outputs rating	50 mA / 12 V DC
Current-carrying capacity of programmable high-current outputs	1100 mA / 12 V DC
AUX output	500 mA / 12 V DC
+VR output	200 mA / 12 V DC
Programmable relay output	1000 mA / 30 V DC
Maximum humidity	93±3%
Messaging telephone numbers	8
Event log	2047
Partitions	2
Timers	4
Power supply rating	2
Enclosure dimensions	266 x 286 x 100
Board dimensions	173 x 105
Operating temperature range	-10...+55 °C
Supply voltage (±15%)	18
Voice messages	16
Current consumption from battery - maximum	340
Current consumption from battery - standby	180
Battery failure voltage threshold (±10%)	11
Battery cut-off voltage (±10%)	10,5
Environmental class according to EN50130-5	II
Current consumption from the 230V network in standby	120
Maximum current consumption from the 230V network	200
Power supply output voltage	12 ±15%
Programmable wired inputs	4