

VERSA-LCDR-WH

The VERSA-LCDR-WH keypad is designed to operate the control panels of **VERSA** and **VERSA Plus** family. Its easy-to-read display and large buttons makes daily operation of the alarm system very convenient even for children and the elderly people. Additionally, the built-in proximity card reader allows control of the system without having to remember the access password. Another useful feature are the function keys, which allow you to quickly enter the selected standby mode or call for help.

- large, easy to read LCD display
- LED indicators of the status of system and partitions
- quick activation of the selected arming mode with dedicated function keys
- PANIC, FIRE, AUX alarms triggered from the keypad
- backlight of display and keys
- audible indication of selected system events
- indication of loss of communication with the control panel
- proximity card reader



Supply voltage	12
Enclosure dimensions	139 x 124 x 22
Operating temperature range	-10...+55 °C
Standby mode current consumption	30
Max. current consumption	65
Weight	240
Maximum humidity	93±3%
Environmental class according to EN50130-5	II
Security grade according to EN 50131	Grade 2